




Description

Larger listening environments require prodigious amounts of power to deliver room filling sound. That's exactly what you get with Rotel's 5 x 250 watt power amplifier. Rotel's RMB-1575 is a true high current audiophile design and can double its output to 5 x 500 watts at 4 ohms with all channels driven. Pure muscle alone, however, does not make a superb amplifier. The RMB-1575 excels at extracting all of the smallest audio details from both music and movie soundtracks alike. Best of all, even with its high power capability the RMB-1075 runs relatively cool, extending the components lifespan thanks to its innovative Class D design.

**Note – all Rotel 15 series components may be rack mounted and remotely controlled via RS-232, IR, or 12 volt (depending on model) for complete stealth operation.*

Specifications

Power Output all channels driven	250 watts x 5ch (20-20 kHz, 0.03% THD, 8 ohms) 500 watts x 5ch (20-20 kHz, 0.03% THD, 4 ohms)	Frequency Response	10 - 80 kHz (+/-3dB)
IM Distortion	< 0.03%	S/N Ratio (IHF A)	109 dB
Damping Factor (8 ohms)	400	Power Consumption	600 watts
Gain	27.1 dB	Dimensions (W x H x D)	431 x 144 x 406 mm (17 x 5 5/8 x 16 in)
Input Sens. / Impedance	1.5 V / 8.3 k ohms	Weight	11 kg (24.2 lbs)